



PCR-80



PO Box 29
Grange, QLD 4051



TEL: (07) 3856 1513



qcom.co

QCOM



PCR-80

CB PORTABLE RADIO

FEATURES

- 5 Watt UHF CB Radio
- Capability up to 128 channels
- High/Low Power Selectable VOX function
- CTCSS/DCS
- FM radio (70-108MHz)

APPLICATIONS

- Traffic Control
- Construction
- Recreation
- Schools
- Factories
- Security

QCOM
PCR-80 UHF CB + FM RADIO 5WATT



HAVE A YARN MATE

PCR-80S Single Pack

GENERAL SPECIFICATION

Frequency	420-490MHz
Channel No	128
Channel Spacing	12.5kHz/25kHz 50 Ohm
Antenna Impedance	(high gain antenna)
Mode Of Operation	Simplex or Semi-Duplex
Frequency Stability	*2.5ppm
Operating Voltage	DC 7.2V 1200mAh



PCR-80T Tradies Case (Twin Pack)


TRANSMITTER

Output Power	UHF:5W / 1W
Sensibility	-122dB (12dB SINAD)
Selectivity	>65dB >60dB
Modulation Mode	16K f F3E / 11K f F3E
Audio Power	>0.5W
Maximum Deviation	<5KHz / <2,5KHz
Adjacent Channel Power	>65dB / >55dB
Spurious Radiation	<7uW
Pre-Emphasis Characteristics	6dB
Current	<1.6A (5W)
Intermediation Sensitivity	1-10mV
Intermediation Distortion	<5%

RECEIVER

RF Sensitivity	-122dB (12dB SINAD)
Audio Distortion	<5%
Blocking	>85dB
Intertmediation	>60dB (wide) >55dB (narrow)
Spurious Rejection	<-65dB

- All specifications are subject to change without notice due to continuous development
- Complies with Australia / New Zealand RF standards



QCOM

(07) 3856 1513 | qcom.co

PCR-80 ACCESSORIES

INCLUDED IN THE BOX



Antenna
ANT-80



Battery
LI-80



Belt Clip
BC-80



Remote Speaker Microphone
TY-01



Single Pocket Charger
SPC1-80



Power Adaptor
XIA-P127A-B6533



Short Lanyard



Long Lanyard
LYN1

OPTIONAL EXTRAS



Six Bay Charger
MPC6R-80



Battery Eliminator
(Included in Tradies Case).
BE-80