

LED 2G11



Product Description:

The QCOM brand ballast-compatible PLL Lamp is the fast and simple way to upgrade downlights and commercial luminaires to the energy-saving benefits of LED. This plug-and-play replacement lamp operates off the existing instant or programmed start fixture ballast - no rewiring required.

Designed as a seamless replacement for 36-watt CFL tubes, the LED PLL lamp consumes 50 percent less energy and lasts twice as long as its fluorescent counterpart.

Feature:

1. Lumens: 2100
2. CCT: 2700K, 3000K, 4000K and 5000K
3. Power factor: 0.9
4. Ballast compatible
5. Suitable for enclosed fixtures
6. 2G11 Base

Specifications:

Model	PLL-2G11-18W
Tube Body Material	PC
Nominal Wattage (W)	18W
Lumens Delivered (lm)	2100lm
Effcacy (lm/W)	116lm/W
CRI	80Ra
Color Temperature (K)	2700K/3000K/4000K/5000K
L70 Lifetime (Hrs)	30,000hrs
Input Voltage	AC220-240V (50/60Hz)
Beam Angle	360°
Power Factor	0.9
Operating Temperature	-20 - 45 ° C
Warm-up time (60%)	<0.5s
Base (standard designation)	2G11
Mercury content	0g
Mercury-free	Yes
Type of protection	IP20

Dimension:

